

09/11/00

## MICROELECTRONIC DEVICE FOR STORING INFORMATION AND METHOD THEREOF

### 5 1. BACKGROUND OF THE INVENTION

#### 1.1 FIELD OF THE INVENTION

The present invention relates to electronic and microelectronic devices. In particular,  
10 the present invention relates to a plurality of materials showing a switching phenomenon and a built-in memory by the aid of which a new principle of storing and reading information in memory cells of semiconductor chips and a plurality of fundamental improvements on electronic or microelectronic devices can be achieved.

#### 15 1.2 DESCRIPTION AND DISADVANTAGES OF PRIOR ART

Although the present invention is applicable in a broad variety of microelectronic or electronic applications it will be described with the focus put on an application to memory cells as RAM (Random Access Memory), for example.

20

The need to remain cost and performance competitive in the production of semiconductor devices has caused continually increasing device density in integrated circuits. To facilitate the increase in device density, new technologies are constantly needed to allow the feature size of these semiconductor devices to be reduced.

25

Conventional DRAM cells, whereby DRAM stand for Dynamic Random Access Memory, consist of a transistor and a capacitor mostly made from Silicon dioxide ( $\text{SiO}_2$ ). They need the transistor to control the inflow and outflow of charge stored in the capacitor as the physical quantity exploitable for storing information. Said  
30 transistor also decouples the capacitors from each other. Such DRAM cells have the disadvantage, that information stored therein is volatile and as such can principally be lost on each power supply failure. Further, the time needed to refresh the information

contained in DRAM cells delimits the read and write performance of such cells. Finally, the structure of such a DRAM cell is quite complex due to the required transistor.

- 5 Thus, a change in computer RAM technology beyond conventional DRAM technology would be desirable.

The use of ferroelectric non-volatile RAM (NVRAM) cells would already be a great step forward as information would not be lost on any power failure although the  
10 structure of the memory cell would remain complex, too. In such ferroelectric RAMs the polarization of the bit storing layer is exploited instead of a capacitor's capacity in DRAM cells for defining two different states which can be associated with two different logical values. A long term repetitive switching between two different states of remanent polarization, however, fatigues the ferroelectric properties of the material,  
15 as e.g. lead zirconium titanate (PZT).

In 'Physics Today' July 1998, page 24 a further high permittivity material and a respective semiconductor fabricating technology is proposed which allows the computer industry to use the equipment of its conventional DRAM manufacturing  
20 plants without having to perform basic retooling. It is the so-called high permittivity DRAM technology.

Herein, the charge of a capacitor can be used to store information as it is done in conventional DRAM technology as the polarization of a high permittivity layer  
25 depends linearly on the applied voltage, as required for charging the DRAM capacitors. A high permittivity material as e.g. barium strontium titanate (BST) having a permittivity  $\epsilon_r$  about 500 instead of  $\epsilon_r$  about 4 for silicon dioxide would allow to reduce the space needed for the capacitor as its capacitance is proportional to its area and the magnitude of its permittivity value. This in turn would allow higher integration  
30 levels compared to conventional silicon oxide materials used in DRAM cells as the capacitor's area consumption is large as compared to that of the coupled transistor.

But, nevertheless, as a disadvantage remains that the leakage current is still significant. Thus, refreshing is a must.

Investigations in the sixties at oxide diodes and thin oxide films revealed several 5 phenomena. For example, J. F. Gibbons and W. E. Beadle reports in their article "Switching properties of thin NiO films", Solid-State Electronics, Pergamon Press 1964, Vol. 7, pp. 785-797, about a two-terminal solid-state switch made from a thin film of nickel oxide. After about 100 - 1000 switching cycles, the device could not be switched out of an ON condition with normal switching signal amplitudes. Other tests 10 on oxide diodes were performed whereby switching was induced by applying high voltages. These diodes broke down after a few cycles and became unusable. T.W. Hickmott reports in Applied Physics Letters, Vol. 6, No. 6, on page 106 and in the Journal of Vacuum Science and Technology, Vol. 6, No. 5 on page 828 about bistable switching in Niobium oxide diodes. He noticed that the metal electrode plays an 15 important role. To sum up, the tested devices and materials showed that they were either difficult to control or unreliable.

In US Patent No. 4,931,763 a memory switch is described that bases on metal oxide thin films. The memory switch is irreversible and therefore only switches once. It can 20 be used as connection element in circuits and arrays but not for storing of changing information.

Finally, with increasing integration near and beyond the 1 Gbit chip due to smaller capacitor size the area consumption of the transistor of a memory cell is not negligible 25 anymore. Thus, a great step forward to Ultra Large Scale Integration (ULSI) would be to simplify the structure of a memory cell as much as possible.

### 1.3 OBJECTS OF THE INVENTION

Therefore, an object of the present invention is to provide a robust simply structured, reliable and non-volatile memory cell.

5

It is another object of the present invention to provide a new simpler method for stable storage of information into such a memory cell and a reproducible erasing and reading from it.

- 10 It is another object of the present invention to provide a simply structured and non-volatile memory cell which is able to store more than only two distinct values, i.e., which is usable for multilevel storage.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
21

## 2. SUMMARY AND ADVANTAGES OF THE INVENTION

These objects of the invention are achieved by the features stated in enclosed independent claims. Further advantageous arrangements and embodiments of the  
5 invention are set forth in the respective subclaims.

The basic discovery underlying the present invention concerns a plurality of doped oxide substances including perovskites and related compounds, i.e. materials, for use in microelectronic devices and in electronic circuits and particularly for use in  
10 semiconductor chips which combine both, a switching phenomenon in resistance and a built-in memory.

A microelectronic device can be designed such that it comprises a region between electrodes with switchable ohmic resistance wherein the region is made of a substance  
15 comprising components  $A_x$ ,  $B_y$ , and oxygen  $O_z$ . The ohmic resistance in the region is reversibly switchable between different states by applying different voltage pulses. The different voltage pulses lead to the respective different states. An appropriate amount of dopant(s) in the substance improves the switching, whereby the microelectronic device becomes controllable and reliable.

20

In general and coinciding with the wording of the claims substances are meant comprising components  $A_x$ ,  $B_y$ , and oxygen  $O_z$ , in which substance said component A is a member of Alkaline metals (group IA in the periodic system of elements), or Alkaline Earth metals (group IIA), or Rare Earth elements, or Scandium, or Yttrium,  
25 said component B is a transition metal being member of one of the groups IB to VIII, or a member of one of the groups IIIA, IVA, VA and the substance has a crystalline structure.

Generally, an elementary cell of the corresponding lattice structure comprises a cell  
30 center molecule which is surrounded by a plurality of oxygen-molecules each having in turn a center molecule. Both types of said center locations can principally be taken by either of the component A, or B, respectively. In other words, there are a plurality of

substances, i.e., where chemically appropriate, in which A and B can change their locations. In view of the large plurality of the different usable substances this understanding of the basic formula given above should be stressed in order to assure the intended scope and to conserve clarity and conciseness of the appended claims,  
5 concurrently.

Said substances comprise some specific range of amount of a dopant of one of or a combination of Chromium, Vanadium, or Manganese, or further transition metals.

- 10 In particular, any substance comprising components  $A_x$ ,  $B_y$ , and oxygen  $O_z$ , in which substance said component A is a member of Alkaline metals (group IA), or Alkaline Earth metals (group IIA), or Rare Earth elements, or Scandium, or Yttrium, and said component B is a transition metal being member of one of the groups IB to VIII, or a member of one of the groups IIIA, IVA, VA are substances which are able to solve the  
15 problem underlying to the present invention, when doped with a dopant of one of or a combination of transition metals, in particular but not exclusively with Chromium, Vanadium, or Manganese, the total dopant amount being larger than 0% and smaller than 5%, and preferably about 0.2% when  $(\text{BaSr})\text{TiO}_3$  is doped with Chromium only. Other preferred amounts of dopants are specific for each dopant element used and  
20 substance to be doped.

Having found the appropriate amount of dopant(s), a stable switching behavior required to operate a microelectronic device, such as a memory cell, can be provided. Fast write, read and erase processes, similar to time scales that are reached with conventional dynamic memories, are achievable.

25

Some additional specific requirements should be met by the combination of indices x, y, z in order to find the substances adapted to the present concept. Each of the following items define a subclass of substances which show the desired switching effect:

30

The combinations of indices x, y and z being defined by

$x = n + 2$ ,  $y = n + 1$ ,  $z = 3n + 4$ , with  $n = 0, 1, 2, 3$  reveal the so-called Ruddlesden

Popper phases like e.g.,  $\text{Sr}_2\text{RuO}_4$  (xyz-index sequence 214) or  $\text{Sr}_3\text{Ru}_2\text{O}_7$  (xyz = 327) and others.

The combinations of indices as defined above with  $n = 0$  contain among others a  
 5 separate class of substances which adopt a spinell structure as it is e.g.,  $\text{Mg}_2\text{TiO}_4$  (214),  $\text{Cr}_2\text{MgO}_4$ ,  $\text{Al}_2\text{MgO}_4$  with A and B positions reversed, i.e. the B cations originally indexed by y are located on the position indexed by x and the A cations on the position indexed by y,  
 or substances with x and y indexing B cations only ( $\text{B}_2\text{BO}_4$ ), examples are  $\text{Fe}_2\text{CoO}_4$ ,  
 10  $\text{Fe}_2\text{FeO}_4$  ( $\text{Fe}_3\text{O}_4$ ).

The combinations of indices x, y and z being defined by  
 $x = n + 1$ ,  $y = n + 1$ ,  $z = 3n + 5$ , with  $n = 1, 2, 3, 4$  reveal a separate class of substances  
 which partly provide substances having an oxygen intercalation.

15

The combinations of indices x, y and z being defined by either of:

$$x = 1, y = 1, z = 1,$$

and one of the indices x or y being 0, reveal exemplary substances like BeO, MgO, BaO, CaO, ... NiO, MnO, CoO, CuO, ZnO, or

20

$$x = n, y = n, z = n + 1 \text{ with } n = 1 \text{ or } 2$$

and one of the indices x or y being 0, for  $n=1$ , reveal substances like  $\text{TiO}_2$ ,  $\text{VO}_2$ ,  $\text{MnO}_2$ ,  $\text{GeO}_2$ ,  $\text{CeO}_2$ ,  $\text{PrO}_2$ ,  $\text{SnO}_2$ ,

25 for  $n = 2$ , reveal substances like  $\text{Al}_2\text{O}_3$ ,  $\text{Ce}_2\text{O}_3$ ,  $\text{Nd}_2\text{O}_3$ ,  $\text{Ti}_2\text{O}_3$ ,  $\text{Sc}_2\text{O}_3$ ,  $\text{La}_2\text{O}_3$  or

$$x = n, y = n, z = 2n + 1 \text{ with } n = 2$$

and one of the indices x or y being 0, reveal exemplary substances like  $\text{Nb}_2\text{O}_5$ ,  $\text{Ta}_2\text{O}_5$  and others.

30

The combinations of indices x, y and z being defined by

$$x = n, y = n, z = 3n, \text{ with } n = 1, \text{ or } 2, \text{ or } 3 \text{ reveal a separate class of substances for } n = 1$$

the so-called perovskites, like  $\text{SrTiO}_3$ ,  $\text{BaTiO}_3$ ,  $\text{KNbO}_3$ ,  $\text{LiNbO}_3$ , and others,

for  $n = 2$   $\text{Sr}_2\text{FeMoO}_6$  and similar substances are provided having a (226) index sequence.

5

The combinations of indices  $x$ ,  $y$  and  $z$  being defined by

$x = n + 1$ ,  $y = n$ ,  $z = 4n + 1$ , with  $n = 1$ , or 2 reveal a separate class of substances.

For  $n = 1$  substances having an index sequence (215) like  $\text{Al}_2\text{TiO}_5$ ,  $\text{Y}_2\text{MoO}_5$  and others  
10 are provided, and

$\text{SrBi}_2\text{Ta}_2\text{O}_9$  and similars are provided for  $n = 2$ .

Each of the classes mentioned above can be modified by varying the composition of  
15 the substance in order to achieve that at least one of said components  $A_x$  or  $B_y$ , respectively, is comprised of a combination of elements out of one group or out of several of the corresponding groups of A, and B, respectively.

A further modification is provided by providing a superlattice made by a combination  
20 of structural unit cells and/or sub-unit cells as it is published in 'E. Kaldis et al. (eds.), High-Tc Superconductivity 1996: Ten Years After Discovery, pp. 95-108', having each a different  $n$ , and in which structural unit cells and/or sub-unit cells are each a member of a corresponding homologous series obtained by oxygen intercalation. A further modification is provided by providing a superlattice made by a combination of  
25 structural unit cells and/or sub-unit cells of the Ruddlesden-Popper type structures having each a different  $n$ , and in which said structural unit cells and/or sub-unit cells are each a member of a corresponding homologous series. In said lattice modifications lattice structures are formed in which single or multiple transition metal oxygen octahedra layers are separated by one or more block layers consisting of component A  
30 and oxygen.



One preferred member of that plurality of substances is  $\text{Ba}_x\text{Sr}_{1-x}\text{TiO}_3$  with  $0 \leq x \leq 0.7$  and having a dopant amount of Chromium between 0% and 5%, preferably between 0 and 1%, even more preferably about 0.2%.

- 5 Others members of that plurality are materials according to  $\text{Ba}_x\text{Sr}_{1-x}\text{TiO}_3$  with  $0 \leq x \leq 0.7$  and having a dopant of Vanadium between 0% and 5%.

Manganese is a preferred dopant, too, particularly in composition with Chromium or Vanadium.

10

Further members of that plurality are perovskite related compounds with other transition metal cations such as Nb. Further dopants can be transition metal elements and combinations thereof, i.e., elements having their valence electron(s) on the d-orbital, i.e., 3d, 4d, or 5d -orbital.

15

When such a material is used for example as a dielectric layer in a capacitor-like structure to form the microelectronic device, it stays switched in either a high or a low conductivity state depending on a voltage pulse being applied to it until it is switched into the other state by applying a new voltage pulse. Thus, said capacitor-like structure  
20 having such a complex dielectric material has a resistance which can be varied by applying short voltage or, alternatively, short current pulses to the embedding electrodes.

As the most decisive electrical property of such a microelectronic device is the change in resistance depending on a defined, applied voltage pulse between the two terminals  
25 of the microelectronic device, whereby said capacitor-like structure can be regarded as a 'switchable resistor'. Said switching behavior is known to be effectuated by a voltage or current driven hysteresis behavior.

Due to said property it is possible to store digital information by different values of  
30 resistance, i.e., by associating a high resistance state with a logic '0' and a low resistance state with a logic '1'. The actual state and thus the stored information can be read out by a current readout or measuring the leakage current as it is relatively large

with low resistance of the dielectric layer and vice versa. Thus, the leakage current which impedes the performance of prior art DRAM technology can be usefully taken for reading the stored value. According to the invention neither the static charge of a capacitor nor the polarization of any ferroelectric material is needed to be used for  
5 storing information but, instead, its resistance.

Thus, a simple way to store information can be followed by realizing the above mentioned concept.

10 The material usable in connection with the present invention when used for e.g. RAM cells has the advantage, in relation to prior art memory cells, that new cells can be constructed just comprising a single capacitor-like structure device with only one pair of electrode terminals for operating it, i.e. to read from, to write into or to erase without a transistor arrangement being necessarily coupled with a capacitor used in prior art to  
15 perform the operating functions of a prior art DRAM cell. One terminal of such a cell is connected to ground and the other is used for writing, erasing or just reading.

Thus, RAM cells can be constructed to use considerably less space on a chip and considerable less manufacturing steps.

20

Further, the usable material has a remarkable high retention time of at least several months with no power connected and can thus be used as a non-volatile memory. Thus a double advantage can be achieved: first, the full time is available for the read and write processes because the refresh cycles and therefore the refresh circuitry are not  
25 required anymore and, secondly, a data storage security is increased as a loss of power supply does not imply a loss of stored data.

Basically, the memory cell can be operated in either a voltage controlled or in a current controlled regime, i.e. information can be stored by applying voltage pulses or by  
30 applying current pulses. In both cases the information can be read by sensing voltage or current. For purposes of improved clarity of this disclosure, however, only the voltage regime is described in the detailed description down below.

Finally, for example in the voltage controlled mode the current flowing when reading a '1' compared to that one when reading a '0' value is about 20 times larger due to the difference in resistance. This feature can advantageously be used for storing more than 5 only one bit in the same cell. Thus, a plurality of two, three, or more bits can be stored or removed by applying different voltage pulses, single pulses or sequences thereof having different shape, level, or duration or being different in number to write and erase. A sufficiently large distance between the different levels can hereby be maintained.

### 3. BRIEF DESCRIPTION OF THE DRAWINGS

The present invention is illustrated by way of example and is not limited by the shape of the figures of the accompanying drawings in which:

5

Fig. 1 is a schematic drawing of a perovskite oxide capacitor-like structure of a microelectronic device usable as memory cell,

10 Fig. 2 shows current-voltage characteristics of a 300 nm thick Cr doped oxide capacitor-like structure,

Fig. 3a to 3c show the principles of operation of the capacitor-like structure analyzed in Fig. 2 as a memory device,

15 Fig. 4a to 4c show the operation of a further microelectronic device as a multilevel memory device,

Fig. 5a to 5h show results of measurements over an extended time period, and

20 Fig. 6 shows a schematic circuit diagram representing the arrangement of a 4-bit-memory circuit.

#### 4. DESCRIPTION OF THE PREFERRED EMBODIMENT

With general reference to the figures and with special reference to Fig. 1 the essential structure of a microelectronic device 10 having a capacitor-like structure is described 5 in more detail. Such a microelectronic device 10 is useable as a memory cell.

The microelectronic device 10 comprising an oxide base electrode 12 made from  $\text{SrRuO}_3$  and a region 14 with an oxide insulator layer made from  $(\text{BaSr})\text{TiO}_3$  slightly doped with Chromium (Cr) for the insulating material and a metallic (Au) top electrode 10 16 on a  $\text{SrTiO}_3$  substrate 18 was fabricated with pulsed laser deposition. The microelectronic device 10 has a thin film capacitor-like structure.

One terminal 20 is connected to said top electrode 16, the other terminal 22 is connected to said base electrode 12.

15

In an experimental arrangement setup for testing the basic switching behavior and further physical properties of the microelectronic device 10 the insulator layer thickness was 300 nanometers.

20 The insulator layer of the region 14 was doped with Chromium (Cr) at an amount of 0.2%.

The leakage current was measured as it is depicted in the drawing as a function of the bias voltage generated by a DC voltage source 24 between said terminals 20, 22.

25

With respect to Fig. 2a to 2c the leakage current voltage characteristic is illustrated in Fig. 2a linearly, in Fig. 2b with a logarithmic leakage current scale of its absolute amount and in Fig. 2c with both logarithmic scales.

30 For small applied bias voltages like several 10 mV a linear current voltage characteristic (IVC) can be observed. A quadratic dependence of the current from the applied voltage can be seen for moderate applied voltages as several 100 mV.

This IVC shape and behavior can be described as space charge limited current. Larger applied voltages result in an exponential like rise of the leakage current with increasing applied voltages.

5

The capacitor-like structure of the microelectronic device 10 shows a reproducible switching behavior causing a hysteresis loop in the current voltage characteristic, described next below:

10 A large negative bias voltage -negative with respect to the  $\text{SrRuO}_3$  electrode- leads to a sudden increase of the leakage current, depicted at about - 0.8 Volt. Sweeping back to large positive bias voltage the leakage current drops back to a low value again depicted at + 0.7 Volt. Said sudden increase and said sudden drop back of leakage current are essential features for switching and deciding between different states.

15

According to the invention it is possible to operate the microelectronic device 10 as a very simple device or memory device, i.e. memory cell in a RAM due to and with the described underlying switching behavior. This will be illustrated in conjunction with Figs. 3a to 3c and 4a to 4c.

20

Basically, by applying a write voltage pulse to the microelectronic device 10 the system is switched into a low resistance state which can be regarded as storing information. An erase voltage pulse recovers the resistance state of the microelectronic device 10 and the information is removed, i.e. erased.

25

As can be seen in Fig. 3a a series of 300 ms long different voltage pulses depicted as sharp peaks were applied to the electrodes (12,16) of the microelectronic device 10.

A write pulse, also called second voltage pulse 6.1, that here is a negative pulse is used  
30 to write information which after a certain delay is removed by an erase pulse, also called first voltage pulse 5.1, that here is a positive pulse. In general, each first voltage pulse 5.1 leads to a first state 1, a high ohmic state, and on the other hand each second

voltage pulse 6.1 leads to a second state 2, a low ohmic state, as can be seen from Fig. 3a in conjunction with Fig. 3c. Between the repeating voltage pulses 5.1, 6.1 a small negative read voltage 9 is switched on and off periodically to read the information and to simulate a realistic readout process. 120 reading cycles each having a duration of 1 5 sec are performed after each write or erase pulse. This readout procedure is schematically depicted in a better time resolution by the zoomed portion in Fig. 3a.

The readout from the microelectronic device 10 is performed by measuring the leakage current flowing at a small applied voltage of - 0.2 V as it is depicted in Fig. 3b which 10 shows current spikes occurring during write and erase followed by the readout period with currents one order of magnitude lower. Fig. 3c is a leakage current scale enlargement of Fig. 3b and clearly shows the above-mentioned first state 1 and second state 2.

15 Two different resistance states can be clearly separated: The first state 1 around 30 nano Amperes yielding a resistance of  $R = 6.6$  Mega Ohm and the second state 2 having a leakage current of 650 nano Amperes yielding a resistance of  $R = 300$  kilo Ohm. The first state 1 will now be associated with a logic state '0' and the second state 2 with a logic state '1'.

20

The '1' resistance value is 20 times smaller than the '0' value. A clear separation of the two logic states '1' and '0' is thus achieved.

Additionally, this remarkable dependence of the resistance on the applied voltage pulse 25 5.1, 6.1 together with the hysteretic behavior also allows to write different values to the microelectronic device 10 and to read them out with a single pre-specified read-out voltage. This so-called multi-level switching phenomenon is discussed later in more detail.

30 During the experimental measuring runs in this example information was written and erased during 300 ms - the duration of the sharp peaks - and stored for 240 s. The time to write and erase information was a specifically selected experimental parameter but is

not limited by the memory device itself. Therefore, the ultimate speed for the write/erase process is much higher, as shown with reference to Fig. 5.

The time over which information can be stored is much longer than those 240 s measured experimentally, as further measurements confirmed that are shown in Fig. 5.

If one analyzes the switching behavior of such capacitor-like structures with varying Cr doping it can be observed that the switching behavior is more pronounced for slightly Cr doped structures, i.e. the best results are obtained with Cr-doping around 0.2%. For these capacitor-like structures the difference between '0' and '1' was the best with adequate reproducibility.

Summarizing the main aspects of the presented structure having a DC-resistance changing sensitively with the applied voltage pulses and consisting of oxides doped can be operated as a memory device or cell with the following intriguing properties:

First they have a very simple structure because the whole memory cell is a capacitor-like structure. Thus they can be operated with only two terminals with a single terminal for read, write and erase. Thus, they are best adapted for ULSI technology.

Further, the difference in resistance between the '0' value and '1' value is at least one order of magnitude as can be seen from Fig. 3c. As can be seen further from the IVC depicted in Fig. 2a, a large resistance range can thus be exploited to store a plurality of different logical values, i.e., the so-called multilevel switching can be achieved. For this, a plurality of write pulses different in size, etc., as mentioned earlier can be applied to write specific logical values into the memory cell, in order to realize not a binary system but, e.g., a digital decimal system based on 10 different logical values being able to be written into and to be read from said memory cell in subsequent write/read/erase cycles.



Finally, the information is stored over long times which is a remarkable advantage compared to conventional DRAM cells.

Fig. 4a to 4c show the operation of a further microelectronic device, a second memory device, that can be used as a multilevel memory device. Since the Fig. 4a to 4c are related to each other, they will be regarded in context to understand the operation of the second memory device. This second memory device for the sake of simplicity is not depicted but is structured as shown in Fig. 1. The second memory device comprising an oxide base electrode 12 made from  $\text{SrRuO}_3$  and a region 14 made from  $\text{SrZrO}_3$  slightly doped with 0.2% Chromium (Cr) for the insulating material and a metallic (Pt/Ti) top electrode 16 on a  $\text{SrTiO}_3$  substrate 18 was fabricated with pulsed laser deposition again.

As can be seen in Fig. 4a a series of different voltage pulses depicted as sharp peaks were applied to the second memory device. In particular, erase voltage pulses 5, low write pulses 6, medium write pulses 7, and high write pulses 8 were applied in a defined repeating sequence in order to simulate realistic erase and write processes. Each peak of the erase voltage pulses 5 indicates 30 pulses with a duration of 1 ms. A small read voltage 9 were applied appropriately in intervals of 10 s in order to read information. This read voltage 9 is smaller in magnitude than the different voltage pulses 5, 6, 7, 8 applied for switching to different states 1, 2, 3, 4.

Fig. 4b shows the current generated by the different voltage pulses 5, 6, 7, 8 and Fig. 4c the current readout enlargement of Fig. 4b. Different states 1, 2, 3, 4 corresponding to different ohmic resistances can be clearly derived from Fig. 4c. The ohmic resistance of the region 14 of the second memory device can be regarded as 'high' after one erase pulse 5 has been applied, that means that the second memory device then stores a high ohmic state, also referred to as first state 1. Conversely, each low write pulse 6 leads to a second state 2, each medium write pulse 7 leads to a third state 3, and each high write pulse 8 leads to a fourth state 4 whereby this fourth state 4 is the lowest ohmic state. The second state 2 and the third state 3 are in-between the high ohmic and the lowest ohmic state. As can be seen in Fig. 4a erase pulses 5 were applied between the write

pulses 6, 7, 8 to switch respectively from the second state 2, the third state 3, or the fourth state 4 to the first state 1.

With each of the different states 1, 2, 3, 4 a corresponding logical value can be associated, e.g., the first state 1 corresponds to logical '00', the second state 2 corresponds to logical '01', the third state 3 corresponds to logical '10' and the fourth state 4 corresponds to logical '11', representing a 2 bit memory cell. In general, more states are possible than the depicted four different states 1, 2, 3, 4.

The erase voltage pulses 5 are here negative voltage pulses whereas the write pulses 6, 7, 8 are positive pulses. Basically, before a memory device is used the first time, an initializing voltage should be applied to polarize this device. Depending on this polarization the erase voltage pulses might either be positive and the write pulses negative or the erase voltage pulses are negative and the write pulses are positive.

15 It shows advantageously, if each of the erase pulses 5 has an equal or smaller magnitude of the amplitude of the write pulses 6, 7, 8.

Contrary to the example, the erase pulses 5 can have different amplitudes for switching directly from the fourth state 4 to the different states 3, 2, 1 having higher ohmic resistance. That means, in particular, for switching from a low ohmic state, that here is the fourth state 4, to a higher ohmic state, e.g. the third state 3, the second state 2, or even the first state 1, the erase pulses 5 have an adapted step-like increased amplitude. Also possible in such a way is a switching from the fourth state 4 directly to the second state 2.

25

The switching behavior of the multilevel memory device was investigated and tested at 77 K, whilst the same switching behavior can be realized at room temperature.

Fig. 5a to 5h show results of measurements over an extended time period on another microelectronic device, a third memory device. This third memory device has the same structure as the second memory device as described above with the exception that the top electrode 12 comprises Au.

In general, within the uppermost row of figures the applied voltages are depicted whilst in the bottom row of figures the resulting current readouts are shown. Fig. 5a indicates two erase pulses 5 and three write pulses 6, each of a duration of 1  $\mu$ s and applied in 5 intervals of 1 min. The current readout with the corresponding states 1, 2 are depicted in Fig. 5b. A third positive write pulses 6 on the 28.4.99 led to a switch from the first state 1 to the second state 2, as can be seen from the figures. After that, the third memory device was stored without any power connection and not used for a longer period of time. Fig. 5c and 5d indicate unperiodical measurements within a time period 10 of two month, whereby the measuring dates are listed in Fig. 5d. More particular, Fig. 5c indicates the read voltage pulses 9 whereas Fig. 5d depicts the current readout result. The result shows that the second state 2 was stored over a longer period of time and thus the third memory device can be regarded as non-volatile for this time period. Fig. 5e shows further write and erase pulses, respectively, and Fig. 5f the resulting 15 states. Finally, Fig. 5g and 5h indicates further unperiodical measurements within a time period of three month, whereby the measuring dates are named in Fig. 5h. On one hand Fig. 5g depicts the read voltage pulses 9 again whereas on the other hand Fig. 5h shows the resulting current readout. The measurements show again that the last information stored in the third memory device was stored over a longer period of time 20 without any decay.

With reference to Fig. 6 a schematic circuit diagram representing the arrangement of a 4-bit-memory circuit is shown.

25 Four microelectronic devices 10, also referred to as memory cells 10, are arranged linearly in order to represent the 4-bit-memory circuit addressed via an address line 28 by a decoder 30 the outputs of which are connected to a respective top electrode 16, as shown in Fig. 1. The base electrodes 22 thereof are each connected to ground. A write, erase, or read voltage pulse can be applied to a selected memory cell 10 through a bias 30 line 32. The different memory cells output current is evaluated through the output line 34.

In a similar way a matrix like arrangement can be achieved by connecting the base electrodes 22 of a row of the memory cells 10 with a further decoder.

It is obvious that the arrangement of the particular components 12, 14, 16, 18 of the 5 capacitor-like structure on a chip, as shown in Fig. 1, will be adapted to the requirements imposed by the specific integration level which is intended to be achieved with the chip. A broad spectrum of different architectures can thus be realized.

Beside the capability of the memory cells 10 described above to store information it is 10 possible to use a system comprising an doped capacitor-like structure as an active switching element in electric or electronic circuits.

In this area of interest a switching operation is not restricted to a specific resistance value. Devices having a resistance of some Mega Ohms can be operated at a voltage 15 between 1 Volt and 5 Volt for writing and erasing and at a voltage between 0.05 Volt and 0.5 Volt for reading. Devices having a smaller resistance can also be operated, however at different voltages.

Further, the present concept is suitable for an application of the substance for 20 constructing EEPROMs (Electrically Erasable Programmable Read Only Memories), logic gates as e.g. AND gates, OR-gates, tunable capacitors and further complex logic circuits.

Particularly, when silicon (Si) or other semiconductor substrates are taken as substrate 25 material instead of strontium titanate the current prior art semiconductor materials can be grown on the substrate thus providing the ability to join conventional semiconductor technology with the memory cells or switching elements, respectively, of the present concepts.

30 In the foregoing specification the invention has been described with reference to a specific exemplary embodiment thereof. It will, however, be evident that various modifications particularly relative to the application of a large variety of different

substances as they are mentioned in the appended claims may be made thereto without departing from the broader spirit and scope of the invention as set forth in the appended claims.

- 5 The specification and drawings are accordingly to be regarded as illustrative rather than in a restrictive sense.

In particular the thickness of the region 14 as well as the lateral dimensions of a memory cell and the applied bias voltages or bias currents, respectively, can be varied  
10 as it is required by any specific purpose imposed by any of a plurality of varying chip designs.

Also the material selection for the bottom electrode can be varied as well. A simple metal like platinum (Pt) is suited as well.

15

Also for the top electrode the material can be varied as well. Au, Pt are suited materials, but principally, all metals and conducting oxides are suited materials for both, top and bottom electrodes.